

PLANE EASY FOAM PLANING TOOLS

www.planeeasy.net

REQUIREMENTS

AIR MOTOR: 1) The air motor operates most efficiently when air pressure is maintained at 125psi. An air compressor able to deliver 23.0cfm is necessary. 2) Incoming air should be DRY, clean, and filtered. We recommend a 3/4" line from the compressor. The last 20' use 1/2" airline. 3) Lubricate this tool daily before using by pouring a small quantity of air tool oil through the air inlet and run tool for a moment to clean. 4) Follow air source manufacturers' directions for connection of regulators, filters and other accessories to air source. 5) Be sure air in "off" position when connecting tool to air supply. 6) Be sure to disconnect tool from air supply before changing accessories, performing maintenance or not in use. **ELECTRIC MOTOR:** 1) During use of this tool, user should blow the dust out of the motor every 30 minutes or more, which also allows the motor to cool down, to prevent burning up the motor. 2) We recommend covering the motor with a sock or something equivalent to help protect the filter and prevent burning up the motor. 3) We also recommend using a 10-gauge power cord with this unit. 4) Be sure to disconnect tool from electric supply before changing accessories, performing maintenance or not in use. 5) Electric motor model is not interchangeable with wire brush or carbide blade fillers. Calman cannot be held responsible for injury or damage if customer uses filler cartridges that are not approved for use with this tool. 6) Calman highly recommends use of vacuum attachment to minimize the dust particles.

SAFETY

Although every effort has been made to make the foam planers as safe as possible, it is the responsibility of the user to wear appropriate safety gear. Full face respirator and eye protection is a must. As with any power tool, use common sense when operating. Do not wear loose clothing or jewelry that could become caught by moving parts, causing injury. We are not responsible for injury.

WARRANTY

J. Calman Industries LLC, warrants this product to be free from defects in materials and workmanship under normal use and service. A defective product may be returned for a free replacement within 30 days of purchase, provided the tool is returned to J. Calman Industries LLC immediately after discovery of the defect. Customer satisfaction is a priority. If you are not 100% satisfied with this tool, customer may return product within 14 days of purchase, follow instructions below for returning equipment. The electric motor is not guaranteed.

VOID OF WARRANTY - This warranty excludes blades, brushes, bolts, bearings and other consumables which must be replaced under normal use and service. This warranty shall not apply to any product or part which is used for a purpose for which it is not designed. All warranties on product become void if there is evidence of tampering, attempted repair, abuse or rework of any part that is not authorized by Calman Industries in writing. Read, understand and follow all instructions before operating this tool. Failure to do so may result in personal injury and/or property damage and will void warranty. The electric motor model is designed to be used exclusively with the nylon brush. Calman is exempt from any and all liability resulting from customer use of wire brush or carbide blade filler with the electric model.

RETURNING EQUIPMENT

Contact Calman Industries at 866-570-2833 or your Plane Easy sales representative, to receive a return authorization form, prior to returning the tool. All returns, after the 14 day satisfaction guarantee, will be subject to a twenty-five percent [25%] re-stocking fee. Tools must be carefully and appropriately packaged. Return shipments must be sent and properly insured at the shippers' expense. All defective products must be returned within 14 days of notification. On defective parts, Calman Industries will pay the shipping fees for the return and replacement parts. Customer must enclose a return authorization form to insure proper credit/refund for return.

Revised 10/01/09